


Technical requirements for electronic control gears for LED- / fluorescent- luminaires for connection at INOTEC central battery systems



Manufacturer: <b>OSRAM GmbH</b> <b>Marcel-Breuer-Str. 6</b> <b>D-80807 München</b>	Type / Description:
	Luminaire: EVG: OT FIT 55/220-240 1A0 CS L EL (ident code: AM04352)
	LED:
Project / Place / Project ID:	Specified by: Name: D. Graser
	Company: OSRAM GmbH
	Date: 30.06.2017

Features	Techn. data / INOTEC requirements	Explanation	Fulfilled (Yes / No)
1 Voltage range AC	230V ± 10%	Voltage range in normal mains operation	<b>Yes</b>
2 Voltage range DC	186V - 260V	Possible voltage range in emergency operation	<b>Yes</b>
3 Control gear suitable for "Joker-Voltage" ?	B2-rectification of the AC voltage (without smoothing)	Pulsating DC voltage 	<b>Yes</b>
4 Control gear compatible with change-over time of the system?	Change-over time: 150 - 1000ms	Typical change-over time of INOTEC systems between mains- and battery operation	<b>Yes</b>
5 Starting behavior of the control gear in DC operation	Stable current consumption within 3s	Necessary for individual lamp monitoring (SV)	<b>Yes</b>
6 Control gear complies with the standard: (only for fluorescent lamps)	DIN EN 60929	AC and/or DC-supplied electronic control gear for tubular fluorescent lamps - Performance requirements	<b>Not relevant</b>
7 Control gear complies with the standard: (only for fluorescent lamps)	DIN EN 61347-2-3 (incl. Attachment J)	Particular requirements for AC and/or DC supplied electronic control gear for fluorescent lamps	<b>Not relevant</b>
8 Control gear complies with the standard: (only for LED)	DIN EN 62384	DC or AC supplied electronic control gear for LED modules - Performance requirements	<b>Yes</b>
9 Control gear complies with the standard: (only for LED)	DIN EN 61347-2-13	Lamp control gear - Part 2-13: Particular requirements for DC or AC supplied electronic control gear for LED modules	<b>Yes</b>
10 Control gear complies with the standard:	DIN EN 55015 (Measurement on AC and DC)	Limits and methods of measurement of radio interference	<b>Yes</b>
11 Control gear complies with the standard:	DIN EN 61000-3-2	Electromagnetic compatibility (EMC) - Part 3-2: Limits - Limits for harmonic current emissions (equipment input current ≤ 16 A per phase)	<b>Yes</b>
12 Control gear complies with the standard:	DIN EN 61547	Equipment for general lighting purposes — EMC immunity requirements	<b>(*2)Yes</b>

Note: VDE 0108 is not a standard for ECG, marking is not applicable

Technical requirements for electronic control gears for LED- / fluorescent- luminaires for connection at INOTEC central battery systems



Manufacturer: <b>OSRAM GmbH</b> <b>Marcel-Breuer-Str. 6</b> <b>D-80807 München</b>	Type / Description: Luminaire:
	EVG: OT FIT 55/220-240 1A0 CS L EL (ident code: AM04352)
Project / Place / Project ID:	LED:
	Specified by: Name: D. Graser
	Company: OSRAM GmbH
	Date: 30.06.2017

Features	Techn. data / INOTEC requirements	Explanation	Manufacturer information
13 Nominal current of the control gear with connected illuminant in AC- operation (230V)		Selection guide for the calculation of the max. number of luminaires per circuit	See Table1
14 Nominal current of the control gear with connected illuminant in DC- operation (216V)		Selection guide for the calculation of the necessary battery capacity	See Table1
15 Nominal current of the control gear with connected illuminant in DC- operation (186V und 260V) and pre-set luminous flux	J-SV-Modul/S (5-120W): > 20mA = OK J-SV-Modul.2/S (20-300W): > 70mA = OK J-SV-Modul.3/S (2-30W): > 12mA = OK J-SV-Modul.4/S (18-120W): > 70mA = OK J-SV-Modul.L/S (20-120W): > 20mA = OK J-SV-Modul T/S (20-100W): > 60mA = OK	Selection guide for determination of the monitoring module: The values are not to be undercut within the voltage range 186VDC - 260VDC to recognise a normal working lamp correctly.	See Table1
			See Table1
16 Luminous flux in DC- operation (186V)		Important for the safety lighting design	100%
17 Standby current of the control gear with no illuminant connected or with defective illuminant in DC-operation (186V and 260V)	J-SV-Modul/S (5-120W): < 10mA = n.OK J-SV-Modul.2/S (20-300W): < 45mA = n.OK J-SV-Modul.3/S (2-30W): < 8mA = n.OK J-SV-Modul.4/S (18-120W): < 45mA = n.OK J-SV-Modul.L/S (20-120W): < 10mA = n.OK J-SV-Modul T/S (20-100W): < 50mA = n.OK	Selection guide for determination of the monitoring module: The values are not to be exceeded within the voltage range 186VDC - 260VDC to recognise a lamp failure correctly.	See Table1  (*1)
18 Max. inrush current of the control gear with connected lamp in AC operation (230V)	Max. permitted inrush current per circuit / monitoring module: SK 4x2A: 250A / 500µs SK 2x4A: 250A / 500µs SK 2x3A: 250A / 500µs SK 1x6A: 250A / 500µs J-SV-Modul T/S: 40A / 500µs all other J-SV-modules: 80A / 500µs	Describes the max. inrush current of all ballasts in a circuit, to calculate the maximum contact rating of the circuit	<b>I<sub>peak</sub>=25A</b> <b>TH=200 µs</b> <b>(*3)</b>

Luminaires, which should work as emergency lighting, have to be in accordance with DIN EN 60598-2-22. (Particular requirements - Luminaires for emergency lighting).

(\*1): The J-SV-monitoring modules monitor the current consumption on the primary side of the control gear for LED modules within the specified limits. Failures of individual LEDs (low-impedance) on the secondary side do not inevitably lead to a modification of current consumption on the primary side, and in such cases cannot be detected as a failure.

(\*2): Not to be used in high risk areas, special release required

(\*3): For calculation the inrush current of the monitoring module must be taken into consideration!

Notes:

For the correctness:

*fardberg, 13.07.2017*

Place, Date

**DS D SST**  
*Dr. Kay Schmidt*  
**DS QML A1 & SQM**  
*Bernhard Schemmel*

Signature

Technical requirements for electronic control gears for LED- / fluorescent- luminaires for connection at INOTEC central battery systems



Table1:

Manufacturer: OSRAM GmbH Marcel-Breuer Str. 6 D-80807 München	Product:  <b>OT FIT 55 220-240 1A0 CS L EL</b>	
--	--	--

LED controller type	Values for load range	In in AC-operation (230V) / mA (trms)	In in AC-operation (240V) / mA (trms)	In in DC-operation (186V) / mA (trms)	In in DC-operation (216V) / mA (trms)	In in DC-operation (240V) / mA (trms)	In in DC-operation (260V) / mA (trms)
OT FIT 55 220-240 1A0 CS L EL	Maximum Load /m Uout= 54V Iout= 1050mA	283,66	272,90	335,56	291,36	264,65	244,26
	Minimum Load /m. Uout= 27V Iout= 800mA		124,48			110,91	
	No Load		40,96	0,09		0,09	0,24
	Short Load		41,10	0,08		0,10	0,24

Maximum inrush current for ECG in AC Operation:  $I_{peak}=25A$

$T_H=200\mu s$

